

# 有源差分探头参照表

MODEL	主要特点	频宽	测量范围 (AC p-p)	衰减选择档	输入阻抗 (差动输入)	输入电阻 (单端对地)
DP-25	经济型 (1000V)	25MHz	200mV~1000V	X20,X50, X200	4MΩ 1.7PF	2MΩ 3.4PF
DP-30HS	超高灵敏度型	30MHz	1mV~65V	x1,x2x10	2MΩ 1.7PF	1MΩ 3.4PF
DP-40LV	650V 中低电压用	40MHz	10mV~650V	x10,x20, x100	4MΩ 1.7PF	2MΩ 3.4PF
DP-50	经济型 (6500V)	50MHz	100mV ~ 6500V	x100,x200, x500,x1000	54MΩ 1.25PF	27MΩ 2.5PF
DP-7500	经济型 (7000V)	50MHz	100mV ~ 6500V	x100,x200, x500,x1000	54MΩ 1.25PF	27MΩ 2.5PF
DP-65Pro	经济型 1300V	65MHz	20mV~1300V	x20,x50 x100,x200	4MΩ 1.7PF	2 MΩ 3.4PF
DP-100	高频高压 6500V	100MHz	50mV~6500V	x100,x200, x500,x1000	54MΩ 1.3PF	27MΩ 2.5PF
DP-14K	14KV 高电压用	75MHz	200mV~14KV	x200,x400, x1000,x2000	100MΩ 1.25PF	50MΩ 2.5PF
DP-20K	20KV 超高电压用	20MHz	300mV~20KV	x300,x600, x1500,x3000	100MΩ 1.25PF	50MΩ 2.5PF
PT-5150	超高量测 范围型	150MHz	10mV~10KV	x10,x30,x100 x300,x1000	100MΩ 1.25PF	50MΩ 2.5PF
PT-5200	超高带宽型	200MHz	20mV~2000V	x20,x50 x100,x200	18MΩ 1.7PF	9MΩ 3.4PF
PT-5220	超高电压.高频 100 倍增益专业型	120MHz	30mV~22KV	x30,x100, x300,x1000, x3000	100MΩ 1.3PF	50MΩ 2.5PF
PT-8001	经济型高精度 700V	25MHz	±700	x10 x100	8MΩ 2.75PF	4MΩ 5.5PF
PT-8002	高精度差动 1400V	25MHz	±1400	x100 x1000	8MΩ 2.75PF	4MΩ 5.5PF
PT-8010	高电压差动 7000V	70MHz	±7000	x100 x1000	20MΩ 3.5PF	10MΩ 7PF
PT-8020	超高电压 14000V	70MHz	±14000	x200 x2000	20MΩ 3.5PF	10MΩ 7PF
PT-8101	高频差动 700V	100MHz	±700	x10 x100	8MΩ 3.5PF	4MΩ 7PF
PT-8110	经济型 1400V	100MHz	±1400	x100 x1000	8MΩ 3.5PF	4MΩ 7PF
PT-50	高灵敏度 700V	50MHz	±700	x10 x1	3.2MΩ 3.5PF	1.6MΩ 7PF
PT-51	高精度 1400V	50MHz	±1400	x100 x1	8MΩ 3.5PF	4MΩ 7PF
PT-800	超高频低压 40V	800MHz	±40	x10 x1	200KΩ 1PF	100KΩ 2PF
PT-200	高频低电压 60V	200MHz	±60	x10 x1	1000KΩ 3.5PF	500KΩ 7PF