

有源差分探头参照表

MODEL	主要特点	频宽	测量范围 (AC p-p)	衰减选择档	输入阻抗 (差分输入)	输入电阻 (单端对地)
DP-25	经济型 (1300V)	25MHz	200mV ~1300V	X20, X50, X200	4M Ω 1.7PF	2M Ω 3.4PF
DP-30HS	超高灵敏度型	30MHz	1mV ~65V	x1,x2x10	2M Ω 1.7PF	1M Ω 3.4PF
DP-40LV	650V 中低电压用	40MHz	10mV ~650V	x10,x20, x100	4M Ω 1.7PF	2M Ω 3.4PF
DP-50	经济型 (6500V)	50MHz	100mV ~6500V	x100,x200, x500,x1000	54M Ω 1.25PF	27M Ω 2.5PF
DP-7500	经济型 (7000V)	50MHz	100mV ~6500V	x100,x200, x500,x1000	54M Ω 1.25PF	27M Ω 2.5PF
DP-65Pro	经济型 1300V	65MHz	20mV ~1300V	x20,x50 x100,x200	4M Ω 1.7PF	2M Ω 3.4PF
DP-100	高频高压 6500V	100MHz	50mV ~6500V	x100,x200, x500,x1000	54M Ω 1.3PF	27M Ω 2.5PF
PT-5140	14KV 高电压用	75MHz	200mV ~14KV	x200,x400, x1000,x2000	100M Ω 1.25PF	50M Ω 2.5PF
PT-5120	20KV 超高电压用	20MHz	300mV ~20KV	x300,x600, x1500,x3000	100M Ω 1.25PF	50M Ω 2.5PF
PT-5150	超高量测 范围型	150MHz	10mV ~10KV	x10,x30,x100 x300,x1000	100M Ω 1.25PF	50M Ω 2.5PF
PT-5200	超高带宽型	200MHz	20mV ~2000V	x20,x50 x100,x200	18M Ω 1.7PF	9M Ω 3.4PF
PT-5220	高频高电压差分探头	120mhz	30mV~22KV	X30,x100,x300, X1000,x3000	100M Ω 1.3PF	50M Ω 2.5PF
PT-8001	经济型高精度 700V	25MHz	± 700	x10 x100	8M Ω 2.75PF	4M Ω 5.5PF
PT-8002	高精度差动 1400V	25MHz	± 1400	x100 x1000	8M Ω 2.75PF	4M Ω 5.5PF
PT-8010	高电压差动 7000V	70MHz	± 7000	x100 x1000	20M Ω 3.5PF	10M Ω 7PF
PT-8020	超高电压 14000V	70MHz	± 14000	x200 x2000	20M Ω 3.5PF	10M Ω 7PF
PT-8101	高频差动 700V	100MHz	± 700	x10 x100	8M Ω 3.5PF	4M Ω 7PF
PT-8110	经济型 1400V	100MHz	± 1400	x100 x1000	8M Ω 3.5PF	4M Ω 7PF
PT-50	高灵敏度 700V	50MHz	± 700	x10 x1	3.2M Ω 3.5PF	1.6M Ω 7PF
PT-51	高精度 1400V	50MHz	± 1400	x100 x1	8M Ω 3.5PF	4M Ω 7PF
PT-800	超高频低压 40V	800MHz	± 40	x10 x1	200K Ω 1PF	100K Ω 2PF
PT-200	高频低电压 60V	200MHz	± 60	x10 x1	1000K Ω 3.5PF	500K Ω 7PF