

山特长效机电配置时间表(按负载满载计算)

更新日期: 2004年1月

机型 MODEL	电池电压 (V)	外接电池			供电时间 (min) (满载以瓦特计)	充电电流
		电池容量	组数	每组电池个数		
MT1000S	24	24AH	1组	2	30	6Amax
			2组		68	
			3组		131	
		38AH	1组		52	
			2组		141	
			3组		179	
		65AH	1组		107	
			2组		180	
			3组		283	
		100AH	1组		155	
			2组		272	
			3组		445	
N1000S	48	24AH	1组	4	56	6Amax
			2组		146	
			3组		191	
		38AH	1组		121	
			2组		217	
			3组		351	
		65AH	1组		167	
			2组		335	
			3组		555	
		100AH	1组		240	
			2组		508	
			3组		817	
C1KS	36	24AH	1组	3	44	7Amax
			2组		113	
			3组		160	
		38AH	1组		80	
			2组		168	
			3组		257	
		65AH	1组		141	
			2组		252	
			3组		422	
		100AH	1组		178	
			2组		372	
			3组		568	
C2KS	96	24AH	1组	8	57	8Amax
			2组		148	
			3组		198	
		38AH	1组		124	
			2组		224	
			3组		366	
		65AH	1组		169	
			2组		350	
			3组		565	

山特长效机电配置时间表(按负载满载计算)

更新日期: 2004年1月

机型 MODEL	电池电压 (V)	外接电池			供电时间 (min) (满载以瓦特计)	充电电流
		电池容量	组数	每组电池个数		
C3KS	96	100AH	1组	8	245	8Amax
			2组		519	
			3组		843	
		24AH	1组		38	
			2组		95	
			3组		148	
		38AH	1组		60	
			2组		157	
			3组		224	
65AH	1组	128				
	2组	221				
	3组	350				
100AH	1组	169				
	2组	299				
	3组	519				
C6KS (N+X)	240	24AH	1组	20	53	4.2Amax
			2组		137	
			3组		176	
		38AH	1组		110	
			2组		192	
			3组		300	
		65AH	1组		160	
			2组		294	
			3组		517	
		100AH	1组		221	
			2组		470	
			3组		723	
C10KS/ 3C10KS (N+X)	240	24AH	1组	20	27	4.2Amax
			2组		59	
			3组		121	
		38AH	1组		47	
			2组		131	
			3组		173	
		65AH	1组		96	
			2组		173	
			3组		266	
		100AH	1组		148	
			2组		257	
			3组		404	
		100AH	4组		543	
			5组		698	
			6组		903	
		24AH	1组		14	
			2组		42	
			3组		59	

山特长效机电配置时间表(按负载满载计算)

更新日期: 2004年1月

机型 MODEL	电池电压 (V)	外接电池			供电时间 (min) (满载以瓦特计)	充电电流				
		电池容量	组数	每组电池个数						
3C15KS (N+X)	240	38AH	1组	20	24	4.2Amax				
			2组		69					
			3组		131					
		65AH	1组		46					
			2组		134					
			3组		173					
			4组		236					
			5组		289					
			6组		385					
		100AH	1组		96					
			2组		174					
			3组		257					
			4组		334					
			5组		459					
			6组		543					
		3C20KS (N+X)	240		24AH		1组	20	9	4.2Amax
							2组		27	
							3组		47	
38AH	1组			14						
	2组			47						
	3组			88						
65AH	1组			26						
	2组			94						
	3组			146						
	4组			172						
	5组			216						
	6组			263						
100AH	1组			56						
	2组			147						
	3组			186						
	4组			255						
	5组			296						
	6组			398						
	7组			478						
	8组			539						
				24AH	1组		15			
					2组		43			
					3组		60			
					4组		109			
		5组	138							
		6组	158							
		38AH	1组	26						
			2组	76						
			3组	136						
			4组	166						

山特长效机电配置时间表(按负载满载计算)

更新日期: 2004年1月

机型 MODEL	电池电压 (V)	外接电池			供电时间 (min) (满载以瓦特计)	充电电流				
		电池容量	组数	每组电池个数						
3C3-20KS	384V	65AH	5组	32	197	4.5A				
			6组		250					
			1组		49					
			2组		139					
			3组		176					
			4组		246					
		100AH	5组		297					
			6组		407					
			1组		102					
			2组		176					
			3组		265					
			4组		356					
		3C3-30KS	384V		24AH		1组	32	8	4.5A
							2组		25	
							3组		45	
							4组		57	
							5组		86	
							6组		114	
38AH	1组			14						
	2组			44						
	3组			82						
	4组			125						
	5组			151						
	6组			170						
65AH	1组			25						
	2组			90						
	3组			142						
	4组			170						
	5组			205						
	6组			254						
100AH	1组	54								
	2组	143								
	3组	180								
	4组	247								
	5组	290								
	6组	377								
		24AH	1组		4					
			2组		16					
			3组		30					
			4组		46					
			5组		55					
			6组		70					
		1组	9							

山特长效机电配置时间表(按负载满载计算)

更新日期: 2004年1月

机型 MODEL	电池电压 (V)	外接电池			供电时间 (min) (满载以瓦特计)	充电电流
		电池容量	组数	每组电池个数		
3C3-40KS	384V	38AH	2组	32	28	4.5A
			3组		52	
			4组		85	
			5组		119	
			6组		142	
			65AH		1组	
		2组			53	
		3组			109	
		4组			144	
		5组			165	
		6组			180	
		100AH	1组		38	
			2组		109	
			3组		157	
			4组		181	
			5组		237	
			6组		275	
		3C3-60KS	384V		24AH	
2组	8					
3组	16					
4组	26					
5组	36					
6组	46					
38AH	1组			3		
	2组			14		
	3组			28		
	4组			45		
	5组			58		
	6组			84		
65AH	1组			8		
	2组			25		
	3组			53		
	4组			91		
	5组			123		
	6组			144		
100AH	1组			20		
	2组			55		
	3组			109		
	4组			144		
	5组			166		
	6组			180		
		24AH	1组	<3		
			2组	4		
			3组	10		
			4组	16		

山特长效机电配置时间表(按负载满载计算)

更新日期: 2004年1月

机型 MODEL	电池电压 (V)	外接电池			供电时间 (min) (满载以瓦特计)	充电电流
		电池容量	组数	每组电池个数		
3C3-80KS	384V		5组	32	23	9A
			6组		30	
		38AH	1组		<3	
			2组		9	
			3组		17	
			4组		28	
			5组		41	
			6组		52	
		65AH	1组		<3	
			2组		15	
			3组		30	
			4组		53	
			5组		80	
			6组		108	
		100AH	1组		11	
			2组		38	
			3组		61	
			4组		109	
			5组		137	
			6组		156	